

### Snage kondenzatorskih baterija Struja, Osigurač, Presek Cu provodnika

Snaga baterije [kVAr]	STRUJA $I_n$ [A]	Tromi osigurači [A] $1.6 \times I_n$	Presek Cu provodnika [mm <sup>2</sup> ]
2.5	3.6	6	4x1.5
5	7.2	10	4x1.5
6.25	9.0	16	4x2.5
7.5	10.8	16	4x2.5
10	14.4	20	4x2.5
12.5	18.0	25	4x4
15	21.7	35	4x6
17.5	25.3	35	4x6
20	28.9	50	4x10
25	36.1	50	4x10
27.5	39.7	63	4x16
30	43.3	63	4x16
31.25	45.1	63	4x16
37.5	54.1	80	3x25/16
40	57.7	80	3x25/16
43.75	63.1	100	3x35/16
45	65.0	100	3x35/16
50	72.2	100	3x35/16
52.5	75.8	125	3x50/25
60	86.6	125	3x50/25
62.5	90.2	125	3x50/25
67.5	97.4	160	3x70/35
68.75	99.2	160	3x70/35
75	108.3	160	3x70/35
87.5	126.3	200	3x95/50
93.75	135.3	200	3x95/50
100	144.3	200	3x95/50
112.5	162.4	250	3x120/70
120	173.2	250	3x120/70
125	180.4	250	3x120/70
150	216.5	315	3x185/95
175	252.6	400	2x3x95/50
200	288.7	400	2x3x95/50
225	324.8	500	2x3x120/70
250	346.8	500	2x3x120/70
275	396.9	630	2x3x185/95
300	433.0	630	2x3x185/95
350	505.2	800	2x3x240/120
375	541.3	800	2x3x240/120
400	577.4	800	2x3x240/120